

# HP 81110A 330/165 MHz Pulse/Pattern Generator HP 81104A 80 MHz Pulse/Pattern Generator

## Technical Specifications

### HP 81100 Family of Pulse/Pattern Generators



#### Compatible family

The HP 81110A and HP 81104A pulse/pattern generators belong to the HP 81100 family. All members have the same programming/user interfaces, which are compatible with the well-established HP 8110A. Migration is therefore easy and cost-effective.

#### Signals for testing digital designs and components

The HP 81110A and HP 81104A generate all the standard pulses and digital patterns needed to test current logic technologies (CMOS, TTL, LVDS, ECL, etc.). With the optional second channel, multi-level and multi-timing signals up to 60 MHz can be obtained using the internal channel addition feature.

- Variable pulse parameters in pattern mode as well as in pulse mode.
- Synchronously triggerable.
- Simulation of reflections/distortions.
- Three/four-level codes.

#### Glitch-free timing changes

Now you can sweep your timing values without the danger of spurious pulses or dropouts that could cause measurement errors. (Applies to continuous mode, values < 100 ms, consecutive values between 0.5 and twice the previous value).

#### Reliable measurements

Both models provide clean, accurate pulses with excellent repeatability thus contributing to measurement integrity.

The HP 81110A features self-calibration for more accuracy. It also offers a choice of output modules: the HP 81111A 165 MHz, 10 V module with variable transitions and the HP 81112A 330 MHz, 3.8 V module which has differential outputs and two selectable transition times.

#### Easy-to-use

Features such as the clear graphical display, autoset, help, store/recall, preset TTL/ECL

#### Key Features

- 1 or 2 output channels.
- HP 8110A user interface.
- Variable transitions.
- Up to 10 Vpp (20 Vpp) into 50  $\Omega$  at 165 MHz.
- 5 ps timing resolution.
- 0.01% frequency accuracy.
- 16 kbit patterns per channel.
- Analog channel addition.
- Fully SCPI programmable.
- Board range of trigger and synchronization capabilities.
- Dropout-and glitch-free change of any timing parameters.
- 8.9 cm height, full rack width.
- Graphical display.
- Modular and user-upgradable.

levels, selectable units (such as current/voltage, width/duty-cycle), and load compensation ensure a high level of convenience.

#### Smooth integration into automated test systems

The HP 81110A and HP 81104A can be integrated easily into all phases of test system development. The HP 81104A features 100% upward compatibility, ensuring that growth with future needs is as easy as just exchanging the instruments physically. This results in low integration costs, in addition to low costs of ownership through proven hardware reliability.

## Specifications

Specifications describe the instrument's warranted performance. Non-warranted values are described as typical. All specifications apply after a 30 minute warm-up phase with 50  $\Omega$  source/load resistance and separate channels. All specifications are valid from 0°C to 55°C ambient temperature.

## Timing Characteristics

Measured at 50% amplitude at fastest transitions in continuous mode and 50  $\Omega$  source impedance.

| Mainframe<br>Output module                                               | HP 81104A<br>HP 81105A                             | HP 81110A<br>HP 81111A                                                                           | HP 81110A<br>HP 81112A                                                                                           |
|--------------------------------------------------------------------------|----------------------------------------------------|--------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------|
| Frequency range<br>from 1 K $\Omega$ <sup>[1]</sup>                      | 1 mHz to 80 MHz<br>Up to 50 MHz typ.               | 1 mHz to 165 MHz<br>Up to 60 MHz typ.                                                            | 1 mHz to 330 MHz<br>N/A                                                                                          |
| Timing resolution                                                        | 3.5 digits, 5 ps best case                         |                                                                                                  |                                                                                                                  |
| RMS jitter (period, width, delay)<br>With PLL<br>With VCO <sup>[2]</sup> | $\pm 0.001\% \pm 15$ ps<br>$\pm 0.01\% \pm 15$ ps  |                                                                                                  |                                                                                                                  |
| Period range                                                             | 12.5 ns to 999.5 s                                 | 6.06 ns to 999.5 s                                                                               | 3.03 ns to 999.5 s                                                                                               |
| Accuracy with PLL                                                        | $\pm 0.01\% (\pm 5\%)$ <sup>[2]</sup>              | $\pm 0.01\% (\pm 0.5\%$ typ. after self-cal., $\pm 3\%$ without self-cal.) <sup>[2]</sup>        |                                                                                                                  |
| Width range                                                              | 6.25 ns to (period - 6.25 ns)                      | 3.03 ns to (period - 3.03 ns)                                                                    | 1.515 ns to (period - 1.515 ns)                                                                                  |
| Accuracy                                                                 | $\pm 5\% \pm 250$ ps                               | $\pm 0.5\% \pm 250$ ps typ. <sup>[3]</sup> $\pm 3\% \pm 250$ ps <sup>[4]</sup>                   |                                                                                                                  |
| Add. variable delay range <sup>[5]</sup>                                 | 0 ns to (period - 12.5 ns)                         | 0 ns to (period - 3.03 ns)                                                                       |                                                                                                                  |
| Accuracy <sup>[6]</sup>                                                  | $\pm 5\% \pm 0.5$ ns                               | $\pm 0.5\% \pm 0.5$ ns typ. <sup>[3]</sup> $\pm 3\% \pm 0.5$ ns <sup>[4]</sup>                   |                                                                                                                  |
| Double pulse delay range                                                 | (width + 6.25 ns) to<br>(period - width - 6.25 ns) | (width + 3.03 ns) to<br>(period - width - 3.03 ns)                                               | (width + 1.5 ns) to<br>(period - width - 1.5 ns)                                                                 |
| Min. period                                                              | 25 ns (40 MHz) typ.                                | 12.2 ns (82 MHz) typ.                                                                            | 6.06 ns (165 MHz) typ.                                                                                           |
| Accuracy                                                                 | $\pm 5\% \pm 250$ ps                               | $\pm 0.5\% \pm 150$ ps typ. <sup>[3]</sup> $\pm 3\% \pm 150$ ps <sup>[4]</sup>                   |                                                                                                                  |
| Transition time range (10/90)                                            | 3 ns to 200 ms variable                            | 2 ns to 200 ms variable                                                                          | 0.8 ns or 1.6 ns selectable                                                                                      |
| Minimum (with overprogramming)                                           | $\leq 3$ ns                                        | $\leq 2$ ns/1.4 ns typ. for<br>ECL levels (20/80)<br>5 ns typ. for 1 K $\Omega$ source<br>imped. | $\leq 600$ ps for $V_{pp} \leq 1$ V<br>450 ps typ. for<br>ECL levels (20/80)<br>$\leq 900$ ps for $V_{pp} > 1$ V |
| Accuracy                                                                 | $\pm 10\% \pm 200$ ps                              |                                                                                                  |                                                                                                                  |
| Linearity                                                                | 3% typ. for transitions > 100 ns                   |                                                                                                  | N/A                                                                                                              |

### Notes:

[1] Source impedance is selectable from 50  $\Omega$  or 1 K $\Omega$  for the HP 81105A and HP 81111A.

[2] If the startable oscillator (VCO) is used (PLL not active).

[3] After self-calibration.

[4] Without self-calibration.

[5] 0 ns to (period - 17.6 ns) in ext. width mode.

[6] Changing of amplitude may add 0.5 ns.

**Burst count:** 2 to 65536 (single or double pulses).

**Delay:** delay, phase, or % of period.

**Double pulse and delay:** mutually exclusive.

**Duty cycle:** set between 0.1% and 95% (subject to width limits. 99.9% with overprogramming).

**Transition times:** leading/trailing edge or % of width.

Leading and trailing edges are independent (HP 81111A/HP 81105A) within one of the following overlapping segments (1:20 ratio): 2 ns (3 ns) - 20 ns, 10 ns - 200 ns, 100 ns - 2 ms, 1  $\mu$ s - 20  $\mu$ s, 10  $\mu$ s - 200  $\mu$ s, 100  $\mu$ s - 2 ms, 1 ms - 20 ms, 10 ms - 200 ms.

**Output timing fidelity:** period, delay, and width are continuously

variable without any output glitches or dropouts.

**Repeatability:** is typ. four times better than accuracy.

**Overprogramming:** all parameters of the HP 81110A, except transitions, can be set to whatever the 330 MHz timing system will allow. This applies also when the HP 81111A output module is used.

## Level/Pulse Performance Characteristics

Level specifications are valid after a 5 ns (HP 81112A) or 30 ns (HP 81111A/HP 81105A) typical settling time.

| Mainframe<br>Output module                                                 | HP 81104A<br>HP 81105A                                          | HP 81110A<br>HP 81111A                                          | HP 81110A<br>HP 81112A                     |
|----------------------------------------------------------------------------|-----------------------------------------------------------------|-----------------------------------------------------------------|--------------------------------------------|
| Amplitude 50 $\Omega$ into 50 $\Omega$<br>1 K $\Omega$ into 50 $\Omega$    | 100 mVpp to 10.0 Vpp<br>200 mVpp to 20.0 Vpp                    |                                                                 | 100 mVpp to 3.8 Vpp<br>N/A                 |
| Level window 50 $\Omega$ into 50 $\Omega$<br>1 K $\Omega$ into 50 $\Omega$ | -10.0 V to +10.0 V<br>-20.0 V to +20.0 V                        |                                                                 | -20 V to +3.8 V<br>N/A                     |
| Accuracy 50 $\Omega$ into 50 $\Omega$<br>1 K $\Omega$ into 50 $\Omega$     | $\pm (3\% + 75 \text{ mV})$<br>$\pm (5\% + 150 \text{ mV})$ [1] | $\pm (1\% + 50 \text{ mV})$<br>$\pm (1\% + 100 \text{ mV})$ [1] | $\pm (2\% + 50 \text{ mV})$<br>N/A         |
| Resolution 50 $\Omega$ into 50 $\Omega$<br>1 K $\Omega$ into 50 $\Omega$   | 10 mV<br>20 mV                                                  |                                                                 | 10 mV<br>N/A                               |
| Output connectors                                                          | BNC single-ended                                                |                                                                 | BNC differential                           |
| Source impedance                                                           | Selectable 50 $\Omega$ or 1 K $\Omega$                          |                                                                 | 50 $\Omega$ only                           |
| Accuracy                                                                   | Typ. $\pm 1\%$                                                  |                                                                 |                                            |
| Max. external voltage                                                      | $\pm 24 \text{ V}$                                              |                                                                 | -2.2 V to +5.5 V                           |
| Short circuit current                                                      | $\pm 400 \text{ mA max.}$<br>(doubles for channel addition)     |                                                                 | -84 mA to +152 mA                          |
| Dynamic crosstalk                                                          | < 0.1% typ.                                                     |                                                                 |                                            |
| Baseline noise                                                             | 10 mV RMS typ.                                                  |                                                                 | 4 mV RMS typ.                              |
| Overshoot/preshoot/ringing                                                 | $\pm 5\%$ of amplitude $\pm 20 \text{ mV}$                      |                                                                 | $\pm 5\%$ of amplitude $\pm 50 \text{ mV}$ |

Note:

[1] In  $\pm 19 \text{ V}$  level window.

**Level parameters:** voltage or current, high or low level, offset or amplitude.

**Load compensation:** the actual load value can be entered (for

loads  $\neq 50 \Omega$ ) to display actual output values. (Applies to the HP 81105A and HP 81111A only).  
**On/off:** relays connect/disconnect output (HiZ).

**Normal/complement:** selectable.  
**Limit:** programmable high and low levels can be limited to protect the device-under-test.

## Channel Addition

If the instrument is equipped with 2 output modules, channel 2 can be added to channel 1 internally. In this case the second output is disabled. The additional fixed delay on the second channel is typ. 2.5 ns. The following parameters differ from the above specifications if two output modules (HP 81105A/HP 81111A) are added.

| Mainframe                                                                  | HP 81104A with two HP 81105A<br>output modules                              | HP 81110A with two HP 81111A<br>output modules |
|----------------------------------------------------------------------------|-----------------------------------------------------------------------------|------------------------------------------------|
| Amplitude 50 $\Omega$ into 50 $\Omega$<br>1 K $\Omega$ into 50 $\Omega$    | 100 mVpp to 20.0 Vpp<br>200 mVpp to 20.0 Vpp                                |                                                |
| Source impedance                                                           | Selectable from 50 $\Omega$ or 1 K $\Omega$                                 |                                                |
| Level window 50 $\Omega$ into 50 $\Omega$<br>1 K $\Omega$ into 50 $\Omega$ | -20.0 V to +20.0 V<br>-20.0 V to +20.0 V                                    |                                                |
| Max. frequency 50 $\Omega$ channel<br>1 K $\Omega$ channel                 | 60 MHz typ.<br>15 MHz typ.                                                  |                                                |
| Min. transitions 50 $\Omega$ channel<br>1 K $\Omega$ channel               | 2 ns typ. (channel one) 5 ns typ. (channel two)<br>20 ns typ. both channels |                                                |

## Pattern Mode

**Pattern length:** 16 kbit/channel and strobe output.

**Output format:** RZ (return to zero), NRZ (non-return to zero), DNRZ (delayed non-return to zero).

**Random pattern:**  
PRBS  $2^n - 1$ ,  $n = 7, 8, \dots, 14$ .

## Trigger Modes

**Continuous:** continuous pulses, double pulses, bursts (single or double pulses), or patterns.

**External triggered:** each active input transition (rising, falling or both) generates a single or double pulse, burst, or pattern.

**External gated:** the active input level (high or low) enables pulses, double pulses, bursts, or patterns. The last single/double pulse, burst, or pattern is always completed.

**External width:** the pulse shape can be recovered. Period and width of an external input signal is maintained. Delay, levels, and transitions can be set.

**Manual:** simulates an external input signal.

**Internal triggered:** internal PLL replaces an external trigger source. Pulses, double pulses, bursts, or patterns can be set.

## Inputs and Outputs

**Clock input/PLL reference and external input**

**PLL reference:** (BNC connector at rear panel). The internal PLL is locked to an external 5 MHz or 10 MHz reference frequency.

**Clock input:** (BNC connector at rear panel). The output period is determined by the signal at CLK input.

**Ext. input:** used for trigger, gate or external width.

**Input impedance:** 50  $\Omega$ /10 k $\Omega$  selectable.

**Threshold:** -10 V to +10 V.

**Max. input voltage:**  $\pm 15$  Vpp.

**Sensitivity:**  $\leq 300$  mVpp typical.

**Transitions:**  $< 100$  ns.

**Frequency:** dc to max. frequency of output module.

**Min. pulsewidth:** 1.5 ns (as width of output module in external width mode).

**Strobe output and trigger output**

**Strobe output:** user-defined, 16 kbit pattern (NRZ) when in pattern mode.

**Trigger format:** one pulse per period with 50% duty cycle typical.

External mode: 1.5 ns typ. for HP 81110A. 5.9 ns typ. for HP 81104A.

**Level:** TTL or ECL selectable.

**Output impedance:** 50  $\Omega$  typical.

**Max. external voltage:**

-2 V/+7 V.

**Transition times:** 1.0 ns typical for TTL, 600 ps typical for ECL.

## User Interface

**Overprogramming:** all parameters can be overprogrammed (exceeding specifications) to fully exploit the hardware limits.

**Setting check:** warning messages indicate potentially conflicting parameters due to inaccuracy. Error messages indicate conflicting parameters.

**Help key:** displays a context-sensitive message.

**Autoset key:** resolves all timing conflicts.

**Non-volatile memory:** current setting is saved on power-down. Up to nine user settings and one fixed default setting can be stored in the instrument.

**Clear memory:** clears all nine user settings.

**Memory card:** 99 settings can be stored on a 1 MB PCMCIA card (MS-DOS<sup>®</sup>).

## Remote Control

Operates according to IEEE standard 488.2, 1987 and SCPI 1992.0.

**Function Code:** SH1, AH1, T6, L4, SR1, RL1, PP0, DC1, DT1, C0.

**Programming times:** all checks and display off.

Typical delay (HP 81110A with HP 81111A output module) [1]

| Instrument mode | From                 | To                                      | Typ. value         |
|-----------------|----------------------|-----------------------------------------|--------------------|
| External width  | EXT. INPUT           | STROBE/TRIGGER OUT<br>OUTPUT 1/OUTPUT 2 | 8.5 ns<br>19.5 ns  |
| All other modes | EXT. INPUT/CLK INPUT | STROBE/TRIGGER OUT<br>OUTPUT 1/OUTPUT 2 | 12.0 ns<br>26.0 ns |
|                 |                      | STROBE/TRIGGER OUT<br>OUTPUT 1/OUTPUT 2 | 14.0 ns            |

### Note:

[1] Subtract 4 ns from the typ. delay value when referring to OUTPUT1/2 for the HP 81112A output module and add 1 ns when referring to OUTPUT1/2 for the HP 81104A with the HP 81105A output module.

| ASCII command         | Typ. exec. time |
|-----------------------|-----------------|
| One parameter or mode | 30 ms typ.      |
| Recall setting        | 250 ms typ.     |
| 16 k pattern transfer | 600 ms typ.     |

## General

### Operating temperature:

0°C to +55°C.

### Storage temperature:

-40°C to +70°C.

### Humidity: 95% r.h. up to 40°C

ambient temperature.

### EMC: conforms to EN50082-1,

EN 55011, Class A.

### Noise emission: 5.7 bel typical.

### Battery: Lithium CR2477-N.

### Safety: IEC1010, CSA1010.

### Power requirements:

100-240 Vac,  $\pm 10\%$ , 50-60 Hz;

100-120 Vac,  $\pm 10\%$ , 400 Hz.

### Power consumption:

300 VA max.

### Max. dimensions (H \* W \* D):

89 mm \* 426 mm \* 521 mm.

### Weight: 9.2 kg net, 13.8 kg shipping.

### Recalibration period: one year recommended.

### Warranty: three years standard.

## Ordering Information

The minimum configuration for a working instrument consists of a mainframe and one output module. The second output module can be added later. Output modules can be exchanged and retrofitted by the user.

The English Quick Start Guide (81110-91010) and Reference Guide (81110-91011) are supplied with each mainframe for all configurations. A memory card is not included.

### HP 81104A 80 MHz Pulse/Pattern Generator Mainframe

#### Output module:

#### HP 81105A 80 MHz, 10 V

### HP 81110A 330/165 MHz Pulse/Pattern Generator Mainframe

#### Output modules:

#### HP 81111A 165 MHz, 10 V

#### HP 81112A 330 MHz, 3.8 V

**Note:** Only add together output modules of the same module number. A combination of the HP 81111A and HP 81112A in one HP 81110A is not possible.

*All options are orderable with the HP 81104A and HP 81110A mainframes.*

### Accessories

#### Opt UN2 Rear Panel Connectors (instead of front panel)

#### Opt 1CP Rack Mount and Handle Kit (5063-9219)

#### Opt 1CN Handle Kit (5063-9226)

#### Opt 1CM Rack Mount Kit (5063-9212)

#### Opt 1CR Rack Slide Kit (1494-0059)

#### Opt UFH 1 MB SRAM Memory Card (0950-3380)

#### HP 15104A Pulse Adder/Splitter

### Quick Start Guide Language Options

#### Opt ABF French Guide (81110-91210)

#### Opt ABJ Japanese Guide (81110-91510)

#### Opt AB0 Taiwan Chinese Guide (81110-91610)

#### Opt AB1 Korean Guide (81110-91710)

#### Opt AB2 Chinese Guide (81110-91810)

### Additional Documentation Options

#### Opt 0BW Service Manual (81110-91021)

#### 81110-91031 Service Documentation (Component Level)

### Support Options

#### Opt 1BP MIL Std. 45662A Calibration with Test Data

#### Opt UK6 Commercial Cal. Certificate

#### Opt W32 3 year Customer Return Calibration Coverage

#### Opt W34 3 year MIL Calibration Service

#### Opt W50 5 year Customer Return Repair Coverage

#### Opt W52 5 year Customer Return Calibration Coverage

#### Opt W54 5 year Customer Return Calibration Coverage



## Related HP Literature

HP 81100 Family of Pulse/Pattern Generators, brochure, p/n 5967-6236E.

HP 81100 Family of Pulse/Pattern Generators, flyer, p/n 5968-0212E.

HP 81101A Pulse Generators, technical specifications, p/n 5967-6274E (Q4/98).

HP 81130A Pulse/Data Generator, technical specifications, p/n 5967-6237E (Q4/98).

**For more information about the products see:**

<http://www.hp.com/go/dvt>

For more information about Hewlett-Packard test & measurement products, applications, services, and for a current sales office listing, visit our web site, <http://www.hp.com/go/tmdir>. You can also contact one of the following centers and ask for a test and measurement sales representative.

### United States:

Hewlett-Packard Company  
Test and Measurement Call Center  
P.O. Box 4026  
Englewood, CO 80155-4026  
Tel: 1 800 452 4844

### Canada:

Hewlett-Packard Canada Ltd.  
5150 Spectrum Way  
Mississauga, Ontario  
L4W 5G1  
Tel: (905) 206 4725

### Europe:

Hewlett-Packard  
European Marketing Centre  
P.O. Box 999  
1180 AZ Amstelveen  
The Netherlands  
Tel: (31 20) 547 9900

### Japan:

Hewlett-Packard Japan Ltd.  
Measurement Assistance Center  
9-1, Takakura-Cho, Hachioji-Shi,  
Tokyo 192-8510, Japan  
Tel: (81) 426 56-7832  
Fax: (81) 426 56-7840

### Latin America:

Hewlett-Packard  
Latin American Region Headquarters  
5200 Blue Lagoon Drive  
9th Floor  
Miami, Florida 33126  
U.S.A.  
Tel: (305) 267-4245/4220  
Fax: (305) 267-4288

### Australia/New Zealand:

Hewlett-Packard Australia Ltd.  
31-41 Joseph Street  
Blackburn, Victoria 3130  
Australia  
Tel: 1 800 629 485 (Australia)  
Tel: 0 800 738 378 (New Zealand)  
Fax: (61 3) 9210 5489

### Asia Pacific:

Hewlett-Packard Asia Pacific Ltd.  
17-21/F Shell Tower, Times Square,  
1 Matheson Street, Causeway Bay,  
Hong Kong  
Tel: (852) 2599 7777  
Fax: (852) 2506 9285

Data subject to change  
Copyright © 1998  
Hewlett-Packard Company  
Printed in U.S.A. 07/98 (CG)  
**5967-5984E**

